





# **ZP12D2/D4**

12" SUBWOOFER



## **SPECIFICATIONS**

Specifications:	ZP12D2	ZP12D4
Speaker Type	Subwoofer	Subwoofer
Speaker Size	12" (322mm)	12" (322mm)
Impedance	2x2 Ω	2x4 Ω
Power (RMS)	1500 W	1500 W
Power (MAX)	4500 W	4500 W
Voice Coil	3" (75mm)	3" (75mm)
Displacement	3 L	3 L
Mounting Depth	186.5 mm	186.5 mm
Mounting Diameter	281.5 mm	281.5 mm
Outer Diameter	322 mm	322 mm
Weight	11.6 kg	11.6 kg

#### TS PARAMETERS


Specifications:	ZP12D2	ZP12D4
Sensitivity	83.1dB (1W/1m)	84.9dB (1W/1m)
Re	3.6 Ohm	6.4 Ohm
Fs	32.686 Hz	36.289 Hz
Qms	4.710	2.625
Qes	0.643	0.593
Qts	0.566	0.483
Cms	64.539 μM/N	62.527 μM/N
Vas	24.280 L	25.028 L
BL	20.552 Tm	27.522 Tm
Sd	514.72 cm2	530.93 cm2
Mms	367.367 g	307.625 g
Le:	3.498 mH	5.609 mH
EBP:	50.83 Hz	61.2 Hz
Xmax	17.5 mm	17.5 mm



## SUBWOOFER CONNECTIONS

SINGLE SUBWOOFER SYSTEM

WIRED IN PARALLEL




**DUAL SUBWOOFER SYSTEM** 

WIRED IN PARALLEL



SINGLE SUBWOOFER SYSTEM

WIRED IN SERIES





DUAL SUBWOOFER SYSTEM

WIRED IN SERIES - PARALLEL




#### **ZP12 CRITICAL DIMESIONS**







#### **ENCLOSURES**



Specifications:	ZP12D2 (Series)	ZP12D4 (Series)
Displacement	3 L / 0.1ft3	3 L / 0.1ft3
Sealed Enclosure:	20L- 35L / 0.9 - 1.2ft3	Not Recommended

Ported Enclosure Small:	45L / 1.58ft3	45L / 1.58ft3
Tuning	40hz	40hz
Port Area	200cm2 / 31in2	200cm2 / 31in2

Ported Enclosure recommended:	60L / 2.1ft3	60L / 2.1ft3
Tuning	35hz	35hz
Port Area	235cm2 / 36in2	235cm2 / 36in2

#### Disclaimer

Always ensure the subwoofer is securely attached, to avoid movement. PHOENIX GOLD accepts no responsibility for damage or injury in relation to inappropriate securing of this product.

Phoenix Gold Product Warranty

LIMITED WARRANTY ON SUBWOOFERS

Phoenix Gold warrants this product to be free of defects in materials and workmanship for a period of one (1) years from the original date of purchase. This warranty is not transferable and applies only to the original purchaser from an authorized Phoenix Gold dealer. Should service be necessary under this warranty for any reason due to manufacturing defect or malfunction, Phoenix Gold or It's Country distributor / reseller will list it discrized in pear in or replace the defective product with new or re-manufactured product at not have. Damage on the product of the product warranty acceptable, misuse, abuse, product modification or neglect, failure to follow installation instructions, unauthorized repair attempts, misrepresentations by the seller. This warranty does not cover incidental or consequential damages and does not cover the cost of removing or reinstalling the unitity. Consentic damage due to accident or normal wear and test is not covered under warranty.